## 31/08/2016

Current Status:	Baseline
Issue Date:	31/08/2016
Version:	3.0

## **Table of Contents**

1.	Introd	luction	3
1.1	Scone		2
1.2	Histor	ry of Changes	4
1.3	Docur	ment References	4
2.		dure Description	
2.1	New N	Non-Interval Metered Connection - Quotation Acceptance	5
	2.1.1	Process Flow Diagram	5
	2.1.2	Process Flow Diagram Process Description	6
2.2	Accele	erated New Non-Interval Metered Connection - Quotation Acceptance  Process Description  Non-Interval Metered Connection - Registration	8
	2.2.1	Process Description	8
2.3	New N	Non-Interval Metered Connection - Registration	9
	2.3.1	Process Flow Diagram	g
	2.3.2	Process Description	10
	2.3.3	Process Flow Diagram Process Description New Connection Registration Validation	12
2.4	New N	Non-Interval Metered Connection – Energisation & Completion	13
	2.4.1	Process Flow Diagram	13
	2.4.2	Process Description	14

#### 1. Introduction

#### 1.1 Scope

This document describes the Retail Market Procedure for the Registration of a Non-Interval metered new connection in Northern Ireland.

Registration is required both for import sites and for export sites having import capability.

The Procedure applies to Non-Interval metered import sites. It contains the following sub-processes:

- New Non-Interval Metered Connection Quotation Acceptance
  - Describes the standard new connection application, quotation and acceptance process
- Accelerated New Non-Interval Metered Connection Quotation Acceptance
  - Describes the new connection application, quotation and acceptance process which can be applied in exceptional circumstances to shorten the standard process duration
- New Non-Interval Metered Connection Registration
  - Describes the submission and validation of the Supplier Registration Request
- New Non-Interval Metered Connection Energisation and Completion
  - Describes the completion of the meter works related to a new connection

#### This procedure excludes:

- New Interval metered connections. (Refer to MP NI 6 New Interval Metered Connection)
- New unmetered connections. (Refer to MP NI 27 New Grouped MPRN and MG NI 28 New Technical MPRN)
- Registration cancellation by a Supplier. (Refer to MP NI 3 Objections and Cancellations)
- Nomination by Suppliers of contracted generation. (Refer to MP NI 7 Generator Nominations)
- Registration requests received for registered meter point in an energised or de-energised state. (Refer to MP NI 1 Change of Supplier Non Interval Credit and to MP NI 37 Change of Supplier Keypad)

## 1.2 History of Changes

Version	Source of	Description of Change
	Change	
0.1	NIE	Initial Draft
0.2	P Merkens	Updated for MCR 1004
		Website Publication removed to MG NI 23 Supplier Data Requests
0.3	P Merkens	Updated following NIE review and for MCR 1054
0.91	P Merkens	Issued for SIG Workshop
0.92	P Merkens	Updated following SIG Workshop and for MCR 1057
0.93	J-E Smith	Final Draft Issued for Supplier Review prior to SIG Approval
0.94	J-E Smith	Visio Updated – New Non-Interval Meter Connection Registration Diagram
0.95	A Ferguson	Clarification on more than one rejection reason code on 101R
1.0	A Ferguson	Baseline SIG Approval
2.0	A Ferguson	Baseline CDA <b>B</b> oard Approved
		Updated for DR 1110/CRID163
2.1	J-E Smith	CDA Board Approved
		Updated for DR1113/CRID165
		Updated for DR1116/CRID166
	A Ferguson	Updated to reflect MP NI 39 Glossary of Terms
2.1.1	J-E Smith	CDA Board Approved
		Updated for DR1132/CRID177
3.0	NIE Networks	Updated to incorporate change of name from NIE to NIE Networks


## 1.3 Document References

Document Reference	Document name
MP NI 3	Objections and Cancellation
MG NI 23	Supplier Data Requests
MP NI 39	NI Market Procedures – Glossary of Terms

## 2. Procedure Description

## 2.1 New Non-Interval Metered Connection - Quotation Acceptance

#### 2.1.1 Process Flow Diagram



## 2.1.2 Process Description

Step	Role	Action	Interface
1 - 3	Customer	A Customer, or their authorised agent, can contact NIE Networks directly to request an application form for a new Non-Interval metered connection, and NIE Networks will send out the form to the Customer.  Alternatively the Customer can download the application form from the NIE Networks website.  The Customer must complete and sign the form, and return it to NIE Networks along with any additional required documentation, e.g.  • Stamp approved full planning approval for the development (if required)  • Site plan 1:500  • Site location map 1:2500  • Floor plan showing the proposed meter position.  The complete list is defined in the Application Checklist on the application form.	Application Form to NIE Networks
4	NIE Networks	On receipt of a completed, signed application form and all additional documentation, NIE Networks will carry out a design for the connection and send a quotation for the work to the Customer. An MPRN is created but will not at this stage be available to the Market Website.  The quotation letter will contain  Their new MPRN(s)  The connection voltage, agreed MIC, MCC and type of metering to be installed  Information regarding the need to obtain a Supplier before the connection can be energised  Information on where Supplier details can be obtained  The next steps in the process  The quotation is valid for 90 days.  NIE Networks may need to carry out a detailed site survey before issuing the quotation. NIE Networks will make arrangements with the Customer first if this is required.  This design process can take between two and twelve weeks.	Quote to Customer

Step	Role	Action	Interface
		If the Customer changes their requirements and requests another quotation, the original MPRN(s) will be Terminated and new MPRN(s) generated with each new quotation.	
5	Customer	The Customer makes the appropriate payment to NIE Networks.	Payment to NIE Networks
6	NIE Networks	On acceptance of the terms of the quotation by the Customer, and receipt of payment, NIE Networks will move the new MPRN(s) to an Assigned state and details will be made available on the Market Website.	
7-8	NIE Networks	NIE Networks will contact the Customer to agree a date for completion of the necessary site construction and to make the supply live to the cut-out at the Meter Point.  Customer sites will not be energised until a Registration Request from a Supplier for the Meter Point has been accepted by NIE Networks.	Telephone call / Email / Letter to Customer
A1.1	Customer	Before the Customer notifies their chosen Supplier to submit a Registration Request, they should send a completed Connection Card for the Meter Point, signed by their electrical contractor, to NIE Networks.	Connection Card to NIE Networks
A1.2	NIE Networks	NIE Networks will record receipt of the Connection Card to allow the Meter Point to be energised after receipt of a valid Registration Request from a Supplier.	


## 2.2 Accelerated New Non-Interval Metered Connection - Quotation Acceptance

## 2.2.1 Process Description

Step Role Action	
NIE Networks  Where an accelerated New Connection Registration is required by a new Customer who is not aware of the requirement for Registration, e.g. if recently arrived from abroad, NIE Networks will endeavour to accelerate the connection process:  NIE Networks will provide the Customer with the MPRN and advise that they must select a Supplier of their choice  If the Customer has difficulty contacting a Supplier, then NIE Networks may contact their Supplier of choice and request that the Supplier contacts the Customer as soon as possible  NIE Networks will reserve an Appointment, on condition that a Registration is received by an agreed time.  Default Supplier  NIAUR will appoint a default Supplier for each certification class of metering. The default Supplier will be contacted by NIE Networks to provide a Registration Request where no Registration is received from another Supplier.  The default Supplier will be required to submit a Registration Request to NIE Networks to facilitate an accelerated new connection process for a Customer who is unaware of the agreed connection process and requires energisation / Registration ahead of the normal two working day Guaranteed Standard.  The default Supplier will also be required to submit a New Connection Registration Request to NIE Networks where NIE Networks identifies a metered connection at which electricity is consumed but which is not registered to a Supplier and for which a Registration Request is not received from another Supplier within five business days of an MPRN being advised to the Customer by NIE Networks. NIE Networks will in this scenario perform a Fieldwork visit to check and confirm the metering and to collect readings.	

### 2.3 New Non-Interval Metered Connection - Registration

### 2.3.1 Process Flow Diagram



## 2.3.2 Process Description

Step	Role	Action	Interface
1	Supplier	A Supplier may determine the characteristics of a Meter Point by reference to information published on the Market Website (see MG NI 23 Supplier Data Requests).	
		The Supplier will request Registration of a Meter Point by providing an application to NIE Networks via a Registration Request market message, completed in accordance with the message implementation rules. Read Arrangements must not be specified for a new connection.	010 to NIE Networks
		The MPRN will have been provided to the Customer as part of the Quotation Acceptance activities between the customer and NIE Networks.	
		Temporary Supplies	
		Where a temporary supply is for a single domestic property, then it must be registered as a residential new connection. Any other temporary supply must be registered as a commercial new connection. Examples of commercial temporary supplies include:  • Builder's site hut where the service cable will be later removed (two or more dwellings)  • Supply to a commercial property or industrial unit  • Supply to a crane.	
		Default Supplier	
		For accelerated new connections the effective date of the Registration will be the date of installation.	
		For unregistered existing connections the effective date of the registration will be the date of the fieldwork visit. Monies in respect of consumption prior to the effective date will be handled through Revenue Protection procedures.	
2	NIE Networks	NIE Networks will determine that the Registration is a metered New Connection Registration and, if so, validate the Registration (see section 2.3.3 New Connection Registration Validation).	
		A Registration that is received after energisation, other than by a Supplier as required in section 2.2, will be treated as a Registration for a Change of Supplier and will be processed as provided in MP NI 1 Change of	

Step	Role	Action	Interface
		Supplier Non-Interval.	
A1	NIE Networks	Where a New Connection Registration Request market message fails validation NIE Networks will send a New Connection Registration Rejection market message to the Supplier.  The market message will contain one or more Reject Reason codes to indicate the reasons for the rejection.  New Connection Registrations can supersede each other. Where a subsequent valid New Connection Registration Request is received and the Meter Point has not been energised, then the initial registration will be rejected and a rejection message 101R sent to the supplier that initiated the existing process.	101R/102R to Supplier
A2	NIE Networks	Where the Registration Request market message is accepted but there are outstanding actions, NIE Networks will send a New Connection Provisional Acceptance market message to the Supplier.  The market message will contain one or more Provisional Acceptance Completion Requirement Codes to indicate the actions that are awaited, including:  • Energisation is awaited  • Connection Agreement required where the Supply Agreement does not cover customer acceptance of the NIE Networks Connection Conditions.	101P to Supplier
A3	NIE Networks	NIE Networks will complete any outstanding actions.	

#### 2.3.3 New Connection Registration Validation


A New Connection Registration Request for a new Non-Interval metered connection will be rejected and the New Supplier advised if:

- The MPRN does not exist
- The Meter Point status is Terminated. Note that a Registration for a registered site in an energised or de-energised state is treated as Change of Supplier
- The Meter Point Address Postcode provided does not exactly match the data held by NIE Networks; where such data is held by NIE Networks. The matching is case sensitive.
- The Supplier ID is not recognised by NIE Networks
- The Supplier ID and Supplier Unit combination is not recognised by NIE Networks
- The SSAC is not a valid arrangement for the Supplier Unit with respect to the Settlement Class of the Meter Point
- For a keypad metered new connection, the Tariff Configuration Code has not been registered for use by the Supplier or is incompatible with the Meter Configuration Code and the Prepayment Indicator.
- The Supplier has not confirmed that a Supply Agreement exists with the Customer. Where the Supplier has an agency agreement for LV connected Customers this must include a clause to cover Customer acceptance of NIE Networks Connection Conditions
- A Registration Request for a trading site is not consistent with registration data obtained from the SEM-O under SEM Agreed Procedure 1

**Note:** the *NI Market Implementation Guide – Meter Registration* provides validation and allowable values at a message field level.

## 2.4 New Non-Interval Metered Connection – Energisation & Completion

#### 2.4.1 Process Flow Diagram



## 2.4.2 Process Description

Step	Role	Action	Interface
1	NIE Networks	For installation and energisation of all new connections, NIE Networks will contact the Customer, or their authorised agent, directly to arrange an Appointment.	Email / Telephone to Customer
2	NIE Networks	NIE Networks will complete the meter installation and energise the Meter Point.  For keypad new connections NIE Networks will:  Configure the keypad meter tariff in accordance with the Registration Request and Provide a keypad premises card to the Customer when the meter is installed, or, if the keypad premises card is not available at that point, will provide the keypad premises card number to the Customer and will provide the keypad premises card as soon as it is available.  Refer to MP NI 3 Objections and Cancellations for circumstances where NIE Networks will cancel a new connection.	
3 - 4	NIE Networks	NIE Networks will process the meter readings obtained as part of the meter works job completion.  NIE Networks will assign a Load Profile and Estimated Usage Factor (EUF) to the Meter Point.	
5-6	NIE Networks	NIE Networks will complete the Registration process and send a New Connection Registration Acceptance market message to the Supplier.	101 to Supplier
7	NIE Networks	NIE Networks will send the new meter details to the Supplier on a Non-Interval Meter Technical Details market message	332 to Supplier